

# KICKER

# NEW! 2021

## KMA-SERIES

### MARINE SPECIAL AMPS 6-CHANNEL AND MONO

Conformal-Coated Circuit Boards  
to Repel Moisture



Small Footprint to Tuck Out of the Way

316L Stainless-Steel,  
No-Rust Hardware

0-6dB Variable Bass Boost

800.1 Provides Fingertip  
Bass Control from the Helm



Marine-Compliant Terminals



Built-In Variable Crossovers  
for Precise Speaker  
Performance Matching



## WHAT MAKES IT SUPERIOR?

- 600.6 6-Channel Adds a Possible Three Full-Range Zones, or Two Full-Range and a Sub Section
- 800.1 is KICKER's Only True Marine Mono-Channel Amp
- Marine Environment-Ready
- Superior Sound Quality and Bass Power

### Model

### KMA600.6

### KMA800.1

Power (watts/ch) 2 Ohm Stereo:	100x6	-
Power (watts/ch) 4 Ohm Stereo:	50x6	-
Power (watts/ch) 4 Ohm Bridged Mono:	200x3	-
Power (watts/ch) 1 Ohm Mono:	-	800x1
Power (watts/ch) 2 Ohm Mono:	-	600x1
Dynamic Power [watts]	750	1200
Frequency Response (Hz):	10-20k	25-200
KMA.6 Crossover: HP only, variable 0-200Hz (amp 1 and 2); OFF/HP/LP, variable 50-200Hz (amp 3), 12dB/octave		
KMA.1 Crossover: LP only, variable 50-200Hz, 12dB/octave		
KickEQ+™ Bass Boost: all models variable 0-6dB @ 40Hz (600.6 amp 3 only)		
All Models DIMs (in, cm):	H – 2-5/16, 5.9; W – 6-11/16, 17	
Length (in, cm):	13-15/16, 35.3	8-1/16, 20.5
FOR MORE INFO: <a href="http://www.kicker.com/kma-amplifiers">www.kicker.com/kma-amplifiers</a>		



MEMBER OF  
**NMMA**  
National Marine Manufacturers Association



////

////

KICKER 2021